








DC Power Station 72000

???????:

421-22



EAN: 
5705730421228



Sandberg DC Power Station 72000 72,000 mAh / 270 Wh 100W
USB-C PD 22W 2 USB-A QC3.0 12V DC 5V 12V
V USB-C
C MPPT DC LED



 ????:
 www.sandberg.jp

Sandberg DC Power Station 72000



Battery capacity: 24 Ah @ 11.25V = 270 Wh / 72000 mAh @ 3.75V = 270 Wh
Battery type: LiMnFePO ₄ (LMFP)
Lifecycle: 2000+ cycles to 80%
USB-C PD input 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD input 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
DC input: 12V–26V / 100W (MPPT supported)
USB-C PD output 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD output 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-A output 1: 5V/3A, 9V/2A, 12V/1.5A (18W max)
USB-A output 2: 5V/3A, 9V/2A, 12V/1.5A (18W max)
DC output: 9.6V–12.6V / 10A (DC5521)
Max total output power: 268W
LED light: Integrated 6W LED
Weight: Approx. 2.3 kg
Charge time: Approx. 3 hours with 100W PD charger (not included)

Supports pass-through charging with port-specific behavior:
If power is being input via DC IN, then USB-C1 cannot be used for input or output at the same time. Other ports work normally.
If USB-C1 is being used for input, DC IN cannot be used simultaneously. Other ports work normally.
If USB-C2 is used for input, USB-A2 can still provide output at the same time, up to 15W. Other ports work normally.



1 Sandberg DC Power Station 72000
1 12V car socket (male) adapter cable
1 12V car socket (female) adapter cable
1 USB-C to USB-C charging cable, 50 cm
1 Quick guide



	??	????
?? (cm)	15.20	21.70
? (cm)	16.50	20.30
?? (cm)	6.20	10.80
?? (g)	2,312.00	2,573.00



??:
www.sandberg.world/product/dc-power-station-72000



?????: