



DC Power Station 72000

Atuagaq nr.:








421-22



EAN:



5705730421228



Sandberg DC Power Station 72000 tassaavoq illit angallattagaq nukissiorfik, 72,000 mAh / 270 Wh-imik imaqqartoq. Marlunnik 100W USB-C PD-nik nukittuunik port-eqarpoq, marlunnik USB-A QC3.0 port-eqarluni 22W tikillugu, kiisalu 12V DC aniatitsivimmik, taamaattumik laptop, tablet, oqarasuaat, allarpassuillu imaarneqarsinnaapput. Aniatitsiviit tallimat tamarmik ataatsikkut atorineqarsinnaapput! Biilimut 12V socket-imut adapter-it angutivissat arnavissallu peqatigalugit, biilimut atortorissaarutit, nillataartitsivik, imaluunniit pumpi toqqaannartumik attavigeqqissaarneqarsinnaapput. USB-C aamma seqerngup panelia (MPPT) DC input aqqutigalugu imaarneqarsinnaasut tapersorsorlugit. LED lamp-i built-in-ilik peqatigalugu, pinngortitami unnuinerit imaluunniit nukissanik amigaateqarnerit piareersimaffigissavatit.

Paasisaqarnerugit:
www.sandberg.gl



Sandberg DC Power Station 72000

Specifications

Battery capacity: 24 Ah @ 11.25V = 270 Wh / 72000 mAh @ 3.75V = 270 Wh

Battery type: LiMnFePO₄ (LMFP)

Lifecycle: 2000+ cycles to 80%

USB-C PD input 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)

USB-C PD input 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)

DC input: 12V-26V / 100W (MPPT supported)

USB-C PD output 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)

USB-C PD output 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)

USB-A output 1: 5V/3A, 9V/2A, 12V/1.5A (18W max)

USB-A output 2: 5V/3A, 9V/2A, 12V/1.5A (18W max)

DC output: 9.6V-12.6V / 10A (DC5521)

Max total output power: 268W

LED light: Integrated 6W LED

Weight: Approx. 2.3 kg

Charge time: Approx. 3 hours with 100W PD charger (not included)

Supports pass-through charging with port-specific behavior:

If power is being input via DC IN, then USB-C1 cannot be used for input or output at the same time.

Other ports work normally.

If USB-C1 is being used for input, DC IN cannot be used simultaneously. Other ports work normally.

If USB-C2 is used for input, USB-A2 can still provide output at the same time, up to 15W. Other ports work normally.



Emballage paasissutissat

1 Sandberg DC Power Station 72000

1 12V car socket (male) adapter cable

1 12V car socket (female) adapter cable

1 USB-C to USB-C charging cable, 50 cm

1 Quick guide

Angissutsit

	Nioqqutissaq	Pakke
Angissuseq (cm)	15.20	21.70
Angissuseq (cm)	16.50	20.30
Itissuseq (cm)	6.20	10.80
Oqimaassuseq (g)	2,312.00	2,573.00



Nioqqutissaq:

www.sandberg.world/product/dc-power-station-72000

 Sandberg®

Tunisassiaq: