



Survivor Radio All-in-1 2000

Vørunnr.:








421-04



EAN:



5705730421044



The Sandberg Survivor Radio All-in-1 2000 is a compact and robust device that packs a plethora of smart features, all of which are useful whether you're out in nature or in an emergency situation. You get a power bank for charging your smartphone, a speaker, a radio with both AM and FM reception, as well as light functions serving as both a flashlight and a reading lamp. The device can be charged from a standard USB power source, and when you're away from power, you can use the built-in solar panel and the attached crank handle for emergency charging.



Meira kunning:



www.sandberg.world



Sandberg Survivor Radio All-in-1 2000



Serstøður

Powerbank:

Capacity: 2000 mAh (7.4 Wh)

USB-A output: 5V/2A

USB-C input: 5V/2A

Approximate charging time:

By AC charger 5V/1.5A (0-100%): 3 hours

By solar panel (0-25%): 20 hours

By hand crank (0-25%): 5 hours

Radio:

AM: 520 - 1710 KHz

FM: 87.0 - 180.0 MHz

Playtime: Up to 20 hours when only using radio

Solar Panel:

Type: Polycrystalline

Voltage: 5V, 95 mA (0.48W max)

Torch LED: 1,5W

Torch LED intensity: 90 Lumens



Pressu sitatir



Pakkingarupplýsingar

1 Sandberg Survivor Radio All-in-1 2000

1 Quick guide

1 USB-A to USB-C charge cable 50 cm

Skjót vegleiðing: <https://sandberg.world/mt/manual/421-04>

↔ Mát

	Vøra	Pakki
Hædd (cm)	7.70	17.70
Breidd (cm)	14.40	8.60
Dýpd (cm)	4.00	4.70
Vekt (g)	260.00	350.00



Vøra:

www.sandberg.world/product/survivor-radio-all-in-1-2000



Handlari: