

## Sandberg Wireless Multimedia Link



Con il collegamento multimediale wireless Sandberg è possibile trasferire in modo wireless suoni ed immagini dal computer alla televisione. E senza il caos creato dai fili! Il kit consiste in un trasmettitore ed un ricevitore. Il trasmettitore connette l'uscita audio della TV e del computer, mentre il ricevitore collega l'ingresso AV della televisione con i cavi in dotazione. □ È possibile selezionare la frequenza di trasmissione per evitare l'interferenza del segnale da altri apparecchi wireless in casa. □ È anche possibile collegare il trasmettitore alle altre sorgenti audio e video come l'antenna satellitare o il lettore DVD. L'amplificatore a segnali infrarossi incorporato rende possibile controllare a distanza la sorgente della trasmissione anche stando comodamente seduti davanti alla televisione.

Sender: 2,4 GHz A/V Sender Receiver: 2,4 GHz A/V Receiver Frequency: 2400 MHz – 2483 MHz Transmitter power: 10 dBm Indoor range: 10 - 30 m Receiver sensitivity: -85 dBm Channel number: 4 (2414, 2432, 2450, 2468 MHz) Frequency stability:  $\pm 100$  KHz Audio/Video input level: 1 Vp-p Supply voltage: 9 V Power: 90 mA (sender and receiver) Dimension: 125x66x117 mm Operating temperature: -10 °C - +50 °C Remote control the A/V Source with IR extender PLL synthesizer NTSC/PAL video formats available IR auto reflect