



Power Station AC 200

??????:

420-83



EAN:



5

Years
Warranty


172.8
Wh

48000
mAh



Charging status display

PD 100W
DC 5521
USB 18W



230V AC 200W



Powerful lamp

Recharge by:
DC5521 + USB-C

Fast recharge by solar panels with DC5521 port

[illegible]

???:




www.sandberg.jp

Sandberg Power Station AC 200



Battery capacity: 14.4V/12Ah/172.8Wh (3.6V/48000 mAh/172.8 Wh)
1 x AC EU wall socket: 230V AC, 50 Hz (200W max)
1 x DC port (5521) input: 5V-20V/2A (40W max)
2 x DC port (5521) output: 12V/10A (120W max)
2 x USB-A output: 5V/2.1A
1 x USB-A output: QC 5V/3A, 9V/2A, 12V/1.5A (18W max)
1 x USB-C PD in/out: 5V/2.4A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
1 x Lamp with white light, 4W/500 Lumens (Max)
1 x Built-in fan
Weight: 1.6 kg
Charge & discharge temperature: -10~45°
Storage temperature: -20~50°
AC output pure sine wave



1 Sandberg Power Station AC 200
1 AC Adapter 30W (EU plug)
1 Adapter DC-5521 plug to car cigarette-lighter socket
1 Quick guide

??????: <https://sandberg.jp/mt/manual/420-83>



	??	????
?? (cm)	14.40	24.10
? (cm)	18.20	21.40
?? (cm)	10.20	13.40
?? (g)	1,860.00	2,020.00



??:
www.sandberg.world/product/power-station-ac-200



?????: