



Survivor Radio All-in-1 5000

??????:

421-03








EAN:



5
Years
Warranty

5000
mAh

[illegible]

???:





www.sandberg.jp

Sandberg Survivor Radio All-in-1 5000



Powerbank:
Capacity: 5000 mAh (18.5 Wh)
USB-A output: 5V/2A
USB-C input: 5V/1.5A
Approximately charging time:
By AC charger 5V/1.5A (0-100%): 4 hours
By solar panel (0-25%): 20 hours
By hand crank (0-25%): 5 hours
Radio:
AM: 520 - 1710KHz
FM: 87.0 - 108.0 MHz
Playtime: Up to 35hrs when only using Radio
Solar Panel:
Type: Polycrystalline
Voltage: 5V, 95 mA (0.48W max)
Torch LED: 3W
Torch LED intensity Low beam: 64 Lumens



1 Sandberg Survivor Radio All-in1 5000
1 USB charge cable USB-C to USB-A 30cm
1 Quick guide
??????: https://sandberg.jp/mt/manual/421-03



	??	????
?? (cm)	7.70	17.00
? (cm)	14.40	8.20
?? (cm)	4.00	5.00
?? (g)	300.00	400.00



?: www.sandberg.world/product/survivor-radio-all-in1-5000



Sandberg®

?????: