



Laptop Powerbank 20000 PD100W

??????:

421-27

EAN:



5 7 0 5 7 3 0 4 2 1 2 7 3

5

Years
Warranty



Sandberg Laptop Powerbank 20000 PD100W????????????????????????????????USB-C?????100W???????DC???.3V-24V????12V
UPS??PC????????????????????????????74Wh????????????



????:




www.sandberg.jp

Sandberg Laptop Powerbank 20000 PD100W



Capacity: 20000 mAh / 3.7V / 74 Wh
DC1-port input: 5-24V/4A, 96W max
DC1-port output: 3.3V-24V, 96W Max
3.3V-19V 5A Max ; 20V-24V 4A Max (Adjustable by 0.1V steps).
DC2-port output: UPS function 12V/3A, 36W max
USB-C PD input: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD output: 5V/3A, 9V/3A, 12V/3A,15V/3A, 20V/5A (100W max)
USB-A output: 5V/3A, 9V/2A, 12V/1.67A (20W max)
Supports Pass-Through Charging: Yes
Auto power off for low consumption (<150 mA) for USB-C and USB-A output
Always-on-function for DC1 and DC2 output
DC5521 port standard
Charge temperature: 0~45?
Discharge temperature: -10~60?



1 Sandberg Laptop Powerbank 20000 PD100W
1 DC-DC Cable 50 cm (5521)
1 Set Laptop DC connectors 8 pcs.
1 Adapter Cable DC-5521 plug to car cigarette-lighter socket 50 cm
1 USB-C PD 100W Charging Cable 50 cm
1 Quick Guide
1 GPSR Safety guide



	??	?????
?? (cm)	14.00	14.00
? (cm)	9.00	17.00
?? (cm)	2.40	6.00
?? (g)	400.00	600.00



?: www.sandberg.world/product/laptop-powerbank-20000-pd100w



?????: