



Survivor Radio All-in-1 5000

Atuagaq nr.:






421-03



EAN:



5705730421037



The Sandberg Survivor Radio All-in-1 5000 is a compact and robust device that packs a plethora of smart features, all of which are useful whether you're out in nature or in an emergency situation. You get a power bank for charging your smartphone, a Bluetooth speaker, a radio with both AM and FM reception, as well as light functions serving as both a flashlight and a reading lamp. The device can be charged from a standard USB power source, and when you're away from power, you can use the built-in solar panel and the attached crank handle for emergency charging.



Paasisaqarnerugit:



www.sandberg.gl

Sandberg Survivor Radio All-in-1 5000



Specifications

Powerbank:

Capacity: 5000 mAh (18.5 Wh)

USB-A output: 5V/2A

USB-C input: 5V/1.5A

Approximately charging time:

By AC charger 5V/1.5A (0-100%): 4 hours

By solar panel (0-25%): 20 hours

By hand crank (0-25%): 5 hours

Radio:

AM: 520 - 1710KHz

FM: 87.0 - 108.0 MHz

Playtime: Up to 35hrs when only using Radio

Solar Panel:

Type: Polycrystalline

Voltage: 5V, 95 mA (0.48W max)

Torch LED: 3W

Torch LED intensity Low beam: 64 Lumens



Tusagassiutit oqaasii



Emballage paasissutissat

- 1 Sandberg Survivor Radio All-in1 5000
- 1 USB charge cable USB-C to USB-A 30cm
- 1 Quick guide

Piaartumik ilitsersuut: <https://sandberg.gl/mt/manual/421-03>

↔ Angissutsit

	Nioqqutissaq	Pakke
Angissuseq (cm)	7.70	17.00
Angissuseq (cm)	14.40	8.20
Itissuseq (cm)	4.00	5.00
Oqimaassuseq (g)	300.00	400.00



Nioqqutissaq:

www.sandberg.world/product/survivor-radio-all-in1-5000



Tunisassiaq: