



Survivor Radio All-in-1 2000

???? ?? ??????..







421-04



EAN:



5705730421044



The Sandberg Survivor Radio All-in-1 2000 is a compact and robust device that packs a plethora of smart features, all of which are useful whether you're out in nature or in an emergency situation. You get a power bank for charging your smartphone, a speaker, a radio with both AM and FM reception, as well as light functions serving as both a flashlight and a reading lamp. The device can be charged from a standard USB power source, and when you're away from power, you can use the built-in solar panel and the attached crank handle for emergency charging.



?????? ??????????..



www.sandberg.mk



Sandberg Survivor Radio All-in-1 2000



??????????????



?????? ?? ???????



Powerbank:
Capacity: 2000 mAh (7.4 wH)
USB-A output: 5V/2A
USB-C input: 5V/2A
Approximate charging time:
By AC charger 5V/1.5A (0-100%): 3 hours
By solar panel (0-25%): 20 hours
By hand crank (0-25%): 5 hours
Radio:
AM: 520 - 1710 KHz
FM: 87.0 - 180.0 MHz
Playtime: Up to 20 hours when only using radio
Solar Panel:
Type: Polycrystalline
Voltage: 5V, 95 mA (0.48W max)
Torch LED: 1,5W
Torch LED intensity: 90 Lumens



???????????? ?? ????????

↔ ????????

1 Sandberg Survivor Radio All-in-1 2000
1 Quick guide
1 USB-A to USB-C charge cable 50 cm
??? ?????: https://sandberg.mk/mt/manual/421-04

	????????	?????
?????? (cm)	7.70	17.70
?????? (cm)	14.40	8.60
???????? (cm)	4.00	4.70
?????? (g)	260.00	350.00



????????:
www.sandberg.world/product/survivor-radio-all-in-1-2000



?????: