

USB-C All-in-1 Docking Station







Varenr.:

136-23

EAN:



5705730136238



Sandberg USB-C All-in-1 Docking Station gir deg mulighet til å koble alt utstyret ditt til din bærbare maskin med bare én USB-tilkobling.

- 3 USB-porter til for eksempel mus, tastatur og ekstern harddisk
 - 3 skjermtilkoblinger, HDMI, DisplayPort og VGA, med mulighet for tilkobling av 2 skjermer samtidig
 - Ethernet-port for ekstremt raskt Gigabyte-nettverk
 - Lydport for hodetelefon og mikrofon
 - Kortleser for minnekort
 - Strømkontakt for USB-C strømforsyning med full styrke på inntil 100 W
- Dokkingstasjon i stilfullt aluminiumsdesign. Kan brukes som et praktisk bordstativ under din bærbare datamaskin.



Flere opplysninger:



www.sandberg.world

Sandberg USB-C All-in-1 Docking Station



Spesifikasjoner

Aluminum case
Laptop connection: USB-C Male
Connectors: 1 x USB-C female (power supporting up to 100W), 1 x HDMI Female, 1 Mini DisplayPort female, 1 x VGA female, 3 x USB 3.0 A female, 1 x RJ45 female, 1 x Audio output
1 x SD card reader slot supporting SD/SDHC/SDXC/MMC
Micro SD/TF card reader slot
RJ45 connector supporting 10/100/1000 Mbps operation
HDMI Resolution up to max 4kx2k @ 30Hz (1920 x 1080P @ 60Hz)
DisplayPort resolution up to 4kx2k @ 30Hz (1920 x 1080P @ 60Hz)
VGA resolution up to 1920x1080P @ 60Hz
Supports HDCP 1.4
Supports simultaneous output at DisplayPort+HDMI and DisplayPort+VGA
Automatic recognition of monitor type, resolution, and features
Supports audio sample rate at 192KHz/24bit
Weight: 329g
Dimensions: 27.5 x 7.3 x 2.1 cm

NOTE: Connection of display devices requires the USB-C port of your device to support Alt Mode.



Pressesitater



Pakkeinformasjon

1 Sandberg USB-C All-in-1 Docking Station
1 Mini DisplayPort to DisplayPort converter

↔ Mål

	Produkt	Pakke
Høyde (cm)	28.00	36.50
Bredde (cm)	8.00	11.50
Dybde (cm)	1.70	3.50
Vekt (g)	233.00	334.00



Produkt:

www.sandberg.world/product/USB-C-All-in-1-Docking-Station



Forhandler: