

Sandberg Wireless Multimedia Link



Met de Sandberg draadloze multimedialink kunt u beeld en geluid draadloos van uw computer naar uw televisiescherm overdragen. Geen gedoe meer met kabels! De kit bestaat uit een zender en een ontvanger. De zender wordt met de TV van uw computer en audio-output verbonden, terwijl de ontvanger de AV-input van uw televisie met de meegeleverde kabels verbindt. U kunt de overdrachtsfrequentie selecteren om storing van signalen van andere draadloze apparatuur in uw huis te voorkomen. U kunt de zender tevens met andere video- en audiobronnen zoals een satellietshotel of dvd-speler verbinden. De ingebouwde infrarood signaalversterker maakt het mogelijk om de bron van de zenderbron te regelen zelfs als u voor de televisie zit.

Sender: 2,4 GHz A/V Sender Receiver: 2,4 GHz A/V Receiver Frequency: 2400 MHz – 2483 MHz Transmitter power: 10 dBm Indoor range: 10 - 30 m Receiver sensitivity: -85 dBm Channel number: 4 (2414, 2432, 2450, 2468 MHz) Frequency stability: ± 100 KHz Audio/Video input level: 1 Vp-p Supply voltage: 9 V Power: 90 mA (sender and receiver) Dimension: 125x66x117 mm Operating temperature: -10 °C - +50 °C Remote control the A/V Source with IR extender PLL synthesizer NTSC/PAL video formats available IR auto reflect