

Sandberg®

DC Power Station 72000

Öge no.:

421-22

Sandberg®
ACTIVE

EAN:



5705730421228



5
Years
Warranty

72000
mAh

100%
Charging status
display

Charge multiple
devices

2 x USB-C
input / output

12V / 10A
output

Powerful
6W LED lamp

Fast recharge by solar panels with DC5521 port

Supports MPPT
solar charging

FC
UK
CA
RoHS
COMPLIANT
CE
WEEE



Sandberg DC Power Station 72000, 72.000 mAh / 270 Wh kapasitesiyle mobil güç merkezinizdir. İki güçlü 100W USB-C PD portu, 22W'a kadar iki USB-A QC3.0 portu ve 12V DC çıkışı ile dizüstü bilgisayarınızı, tabletinizi, telefonunuzu ve daha fazlasını şarj edebilirsiniz. Tüm beş çıkış aynı anda kullanılabilir! Aracın 12V soketi için hem erkek hem de dişi adaptörlerle birlikte gelir, böylece araç ekipmanını, soğutucuyu veya pompayı doğrudan kolayca bağlayabilirsiniz. USB-C ve güneş paneli (MPPT) üzerinden DC girişinden şarj etmeyi destekler. Dahili LED lambası ile kamp yapmaktan elektrik kesintilerine kadar her şeye hazırsınız.



Daha fazla bilgi:



www.sandberg.world

Sandberg DC Power Station 72000

Özellikler

Battery capacity: 24 Ah @ 11.25V = 270 Wh / 72000 mAh @ 3.75V = 270 Wh
Battery type: LiMnFePO₄ (LMFP)
Lifecycle: 2000+ cycles to 80%
USB-C PD input 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD input 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
DC input: 12V-26V / 100W (MPPT supported)
USB-C PD output 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD output 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-A output 1: 5V/3A, 9V/2A, 12V/1.5A (18W max)
USB-A output 2: 5V/3A, 9V/2A, 12V/1.5A (18W max)
DC output: 9.6V-12.6V / 10A (DC5521)
Max total output power: 268W
LED light: Integrated 6W LED
Weight: Approx. 2.3 kg
Charge time: Approx. 3 hours with 100W PD charger (not included)

Supports pass-through charging with port-specific behavior:

If power is being input via DC IN, then USB-C1 cannot be used for input or output at the same time. Other ports work normally.

If USB-C1 is being used for input, DC IN cannot be used simultaneously. Other ports work normally.

If USB-C2 is used for input, USB-A2 can still provide output at the same time, up to 15W. Other ports work normally.



Paketleme bilgileri

1 Sandberg DC Power Station 72000
1 12V car socket (male) adapter cable
1 12V car socket (female) adapter cable
1 USB-C to USB-C charging cable, 50 cm
1 Quick guide

Boyutlar

	Ürün	Paket
Yükseklik (cm)	15.20	21.70
Genişlik (cm)	16.50	20.30
Derinlik (cm)	6.20	10.80
Ağırlık (g)	2,312.00	2,573.00



Ürün:

www.sandberg.world/product/dc-power-station-72000



Bayi: